

Ketho Mirror cabinet # KT7530 R/L

| < 25 5/8" Inch > |



| Mirror cabinet | Dimension | Weight | Order number |
|--|-----------|--------|--------------|
| cIAPMO®ELECTRICAL, 1 mirror door, 1 handle attached, 2 glass shelves, 1 sensor switch bottom right, GFCI outlets are not supplied by the manufacturer (GFCI outlets can be added to the cabinet by a certified electrician on the job site), Mirror cabinets require a GFCI 110 V 60 Hz power source. Flat plug will be supplied with the mirror cabinet, 2 interior lights (fluorescent tube T5 14 W 835 W) | | | |
| Colors | | | |
| M14 Terra (Decor) M18 White Matt M22 White High Gloss (Decor) M31 Pine Silver (Decor) M43 Basalt Matt (Decor) M49 Graphite Matt (Decor) M51 Pine Terra (Decor) M52 European Oak (Decor) M53 Chestnut Dark (Decor) M73 Ticino Cherry Tree (Decor) M79 Natural Walnut (Decor) | | | |
| Variant | | | |
| 25 5/8" x 7 1/8" Inch | | | KT7530 R/L |
| Infobox | | | |
| Handles are included for optional installation on mirror glass, Distance between sensor and reflecting surfaces = minimum 3", Required specification for ordering:, - Hinges left (L) or right (R) | | | |
| | | | |

All drawings contain the necessary measurements which are subject to standard tolerances. They are stated in inch & mm and are non-binding. Exact measurements, in particular for customized installation scenarios, can only be taken from the finished ceramic piece.